HAR	TING

DIN power female contacts – crimp



	Concert information			<u> </u>		<u>.</u>	
	General information						
	Design	IEC 6	50603-2	for typ	es: D, E, F, I	MH 21+4, F9, 2F,	FM 21+24
	Contact resistance	max.	20mOhm				
	Insulation resistance	min.	10GOhm min.	8			
	Working current	see	corresponding connector				
	Temperature range	-55°	C +125°C			-	
5	Insertion and withdrawal force	24pc	ole max. 37N	32pole	max. 50N	48pole max. 751	N
	Mating cycles	- PL	.1 acc. to IEC 60603-2 =>	500 ma	ting cycles		
		- PL	.2 acc. to IEC 60603-2 =>	400 ma	ting cycles		
	UL file	E102	079	1			
	RoHS – compliant	Yes					
	Leadfree	Yes					
	Hot plugging	No					
	Contact material						
	Contact material		per alloy				
	Plating termination zone	Ni					
	Plating contact zone		over PdNi over Ni	-		-	
						-	
	Installation of crimp contacts						
						-	
	contacts should be correctly oriented configuration. They snap into position tensile strength of the contact. Whe	d and inserted into t n and are firmly held	in place. A light pull on the	moulding in the re wire assures the	equired correct		
	contacts should be correctly orienter configuration. They snap into position	d and inserted into t n and are firmly held n using stranded wir slot on the side of th e contact can then b ontact/wire which can	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 r he respective crimp cavity. T be easily withdrawn using a l	moulding in the re wire assures the mm ² an insertion to his action compres light pull on the w	equired correct ool is ses the ire. This		
	contacts should be correctly oriented configuration. They snap into position tensile strength of the contact. Whe necessary. <u>Removing the crimp contacts</u> The removal tool is inserted into a s contact retaining spring therefore th action will cause no damage to the c	d and inserted into t n and are firmly held n using stranded wir slot on the side of th e contact can then b ontact/wire which can	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 r he respective crimp cavity. T be easily withdrawn using a l	moulding in the re wire assures the mm ² an insertion to his action compres light pull on the w	equired correct ool is ses the ire. This		
	contacts should be correctly oriented configuration. They snap into position tensile strength of the contact. Whe necessary. <u>Removing the crimp contacts</u> The removal tool is inserted into a s contact retaining spring therefore th action will cause no damage to the c demonstrates the crimp removal proc	d and inserted into t n and are firmly held n using stranded wir slot on the side of th e contact can then b ontact/wire which can edure (max. 5x).	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 r he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as	moulding in the re e wire assures the mm ² an insertion the ihis action compres light pull on the w s necessary. The d	equired correct ool is ses the ire. This	stripping	g length (mm)
	contacts should be correctly oriented configuration. They snap into position tensile strength of the contact. Whe necessary. <u>Removing the crimp contacts</u> The removal tool is inserted into a s contact retaining spring therefore th action will cause no damage to the c demonstrates the crimp removal proc <u>Dimensions and tensile strength</u> *	d and inserted into t n and are firmly held n using stranded wir slot on the side of th e contact can then b ontact/wire which can edure (max. 5x).	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 n he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as in Insulation Ø [mm]	moulding in the re wire assures the mm ² an insertion the his action compres light pull on the w s necessary. The d Tensile s	equired correct bol is ses the ire. This rawing		<u>g length [mm]</u> 5 +0,5
	contacts should be correctly orienter configuration. They snap into position tensile strength of the contact. Whe necessary. <u>Removing the crimp contacts</u> The removal tool is inserted into a scontact retaining spring therefore thaction will cause no damage to the cdemonstrates the crimp removal procession. Dimensions and tensile strength* Type Wire gauge [n	d and inserted into t n and are firmly held n using stranded wir slot on the side of th e contact can then b ontact/wire which can edure (max. 5x).	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 m he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as in be repositioned/refitted as in be repositioned/refitted as	moulding in the re e wire assures the mm ² an insertion the ihis action compres light pull on the w s necessary. The d Tensile s 11	equired correct bol is ses the ire. This rawing trength [N]	3,	
	contacts should be correctly orienter configuration. They snap into position tensile strength of the contact. Whe necessary. Removing the crimp contacts The removal tool is inserted into a scontact retaining spring therefore thaction will cause no damage to the c demonstrates the crimp removal processory. Dimensions and tensile strength* Type Wire gauge [n] FC 1 0,09 - 0,2!	d and inserted into t n and are firmly held n using stranded wir slot on the side of th e contact can then b ontact/wire which can edure (max. 5x).	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 m he respective crimp cavity. T he easily withdrawn using a l n be repositioned/refitted as <u>i Insulation Ø [mm]</u> 24 0,7 - 1,5 20 0,8 - 2,0	moulding in the re e wire assures the mm ² an insertion the light pull on the w s necessary. The d Tensile s 11 15	equired correct bol is ses the ire. This rawing trength [N] - 28	3,	5 +0,5
	contacts should be correctly oriented configuration. They snap into position tensile strength of the contact. When ecessary. Removing the crimp contacts The removal tool is inserted into a scontact retaining spring therefore thaction will cause no damage to the contacts the crimp removal processors. Dimensions and tensile strength* FC 1 0,09 - 0,21 FC 2 0,14 - 0,56 FC 3 0,5 - 1,5 For the fabrication in line with the science in the science	d and inserted into t n and are firmly held n using stranded wir slot on the side of th e contact can then b ontact/wire which can edure (max. 5x). <u>mm²] AWG</u> 5 28 - 2 5 26 - 2 5 26 - 2 5 20 - 1 pecification, please u see chapter 30 of th	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 m he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as is Insulation Ø [mm] 24 0,7 - 1,5 20 0,8 - 2,0 16 1,6 - 2,8 ise exclusively crimp tools a he catalogue	moulding in the re e wire assures the mm ² an insertion the ihis action compres light pull on the w s necessary. The d Tensile s 11 15 60 pproved by HARTIN	equired correct bol is ses the ire. This rawing <u>trength [N]</u> - 28 - 60 - 135 IG (see DIN E	3,	5 +0,5 5 +0,5
	contacts should be correctly orienter configuration. They snap into position tensile strength of the contact. When ecessary. Removing the crimp contacts The removal tool is inserted into a scontact retaining spring therefore thaction will cause no damage to the codemonstrates the crimp removal processory. Dimensions and tensile strength* Type Wire gauge [m FC 1 0,09 - 0,2! FC 2 0,14 - 0,56 FC 3 0,5 - 1,5 For the fabrication in line with the science in the scin the scin the scin the science in the science in the science in	d and inserted into t n and are firmly held n using stranded wir slot on the side of th e contact can then b ontact/wire which can edure (max. 5x).	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 m he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as i Insulation Ø [mm] 24 0,7 - 1,5 20 0,8 - 2,0 16 1,6 - 2,8 use exclusively crimp tools a	moulding in the re e wire assures the mm ² an insertion the ihis action compres light pull on the w s necessary. The d Interpret descent for the second second second Interpret descent for the second for the second seco	equired correct bol is ses the ire. This rawing trength [N] - 28 - 60 - 135 G (see DIN E Ref.	3, 3, 3, 0 60352-2)	5 +0,5 5 +0,5 5 +0,5
	contacts should be correctly orienter configuration. They snap into position tensile strength of the contact. Whe necessary. Removing the crimp contacts The removal tool is inserted into a scontact retaining spring therefore thaction will cause no damage to the c demonstrates the crimp removal processory. Dimensions and tensile strength* Type Wire gauge [n FC 1 0,09 - 0,2! FC 2 0,14 - 0,56 FC 3 0,5 - 1,5 For the fabrication in line with the s Insertion, removal and crimping tools *Extract from DIN IEC 60352-2, Amer All Dimensions in mm Original Size DIN A4	d and inserted into t n and are firmly held n using stranded wir slot on the side of th e contact can then b ontact/wire which can edure (max. 5x). mm ²] AWG 5 28 - 2 5 26 - 2 5 26 - 2 5 26 - 2 5 26 - 2 6 20 - 7 pecification, please u see chapter 30 of th d. 2, table IV Scale Free s 1:1	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 m he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as in be repositioned/refitted as 24 0,7 - 1,5 20 0,8 - 2,0 16 1,6 - 2,8 use exclusively crimp tools a he catalogue	moulding in the re wire assures the mm ² an insertion the his action compres light pull on the w s necessary. The d Tensile s 11 15 60 pproved by HARTIN	equired correct bol is ses the ire. This rawing trength [N] - 28 - 60 - 135 IG (see DIN E Ref. Sub. DS 09 06 3	3, 3, 3, 3, 0 60352-2)	5 +0,5 5 +0,5 5 +0,5
	contacts should be correctly orienter configuration. They snap into position tensile strength of the contact. When ecessary. Removing the crimp contacts The removal tool is inserted into a scontact retaining spring therefore thaction will cause no damage to the codemonstrates the crimp removal processory. Dimensions and tensile strength* Type Wire gauge [m FC 1 0,09 - 0,2! FC 2 0,14 - 0,56 FC 3 0,5 - 1,5 For the fabrication in line with the science in the scin the scin the scin the science in the science in the science in	d and inserted into t n and are firmly held n using stranded wirk slot on the side of th e contact can then b ontact/wire which can edure (max. 5x).	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 m he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as in be repositioned/refitted as 24 0,7 - 1,5 20 0,8 - 2,0 16 1,6 - 2,8 use exclusively crimp tools an he catalogue size tol.	moulding in the re e wire assures the mm ² an insertion the ihis action compres light pull on the w s necessary. The d Tensile s 11 15 60 pproved by HARTIN	equired correct bol is ses the ire. This rawing <u>trength [N]</u> - 28 - 60 - 135 - 135 - 135 - 135 - 135 - 135 - 135 - 28 - 60 - 135 - 28 - 60 - 135 - 13	3, 3, 3, 3, 0 60352-2) 310 08 01 / EC01557 / 14 State	5 +0,5 5 +0,5 5 +0,5 4.07.2011
	contacts should be correctly orienter configuration. They snap into position tensile strength of the contact. Whe necessary. Removing the crimp contacts The removal tool is inserted into a scontact retaining spring therefore thaction will cause no damage to the c demonstrates the crimp removal processory. Dimensions and tensile strength* Type Wire gauge [n FC 1 0,09 - 0,2! FC 2 0,14 - 0,56 FC 3 0,5 - 1,5 For the fabrication in line with the s Insertion, removal and crimping tools *Extract from DIN IEC 60352-2, Amer All Dimensions in mm Original Size DIN A4	d and inserted into t n and are firmly held n using stranded wirk slot on the side of th e contact can then b ontact/wire which can edure (max. 5x).	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 m he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as is Insulation Ø [mm] 24 0,7 - 1,5 20 0,8 - 2,0 16 1,6 - 2,8 ise exclusively crimp tools a he catalogue size tol. Inspected by Sta TADJE HOF	moulding in the re e wire assures the mm ² an insertion the ihis action compress light pull on the w s necessary. The d Tensile s 11 15 60 pproved by HARTIN pproved by HARTIN if MANN	equired correct bol is ses the ire. This rawing trength [N] - 28 - 60 - 135 IG (see DIN E Ref. Sub. DS 09 06 3	3, 3, 3, 3, 0 60352-2)	5 +0,5 5 +0,5 5 +0,5 4.07.2011 elease Doc-Key / ECM
	contacts should be correctly orienter configuration. They snap into position tensile strength of the contact. Whenecessary. Removing the crimp contacts The removal tool is inserted into a scontact retaining spring therefore thaction will cause no damage to the c demonstrates the crimp removal proce Dimensions and tensile strength* Type Wire gauge [n FC 1 0,09 - 0,21 FC 2 0,14 - 0,56 FC 3 0,5 - 1,5 For the fabrication in line with the science of the science of the contact removal and crimping tools *Extract from DIN IEC 60352-2, Americal Size DIN A4 Operational Size DIN A4 Department EC PD - DE	d and inserted into t n and are firmly held n using stranded wirk slot on the side of th e contact can then b ontact/wire which can edure (max. 5x).	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 m he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as in be repositioned/refitted as 24 0,7 - 1,5 20 0,8 - 2,0 16 1,6 - 2,8 use exclusively crimp tools an he catalogue size tol.	moulding in the re e wire assures the mm ² an insertion the ihis action compress light pull on the w s necessary. The d Tensile s 11 15 60 pproved by HARTIN pproved by HARTIN if MANN	equired correct bol is ses the ire. This rawing <u>trength [N]</u> - 28 - 60 - 135 - 135 - 135 - 135 - 135 - 135 - 135 - 28 - 60 - 135 - 28 - 60 - 135 - 13	3, 3, 3, 3, 0 60352-2) 310 08 01 / EC01557 / 14 State Final Re	5 +0,5 5 +0,5 5 +0,5 4.07.2011
	contacts should be correctly orienter configuration. They snap into position tensile strength of the contact. Whe necessary. Removing the crimp contacts The removal tool is inserted into a scontact retaining spring therefore thaction will cause no damage to the c demonstrates the crimp removal proceed demonstrates the crimp removalemonstrates the crimp removal proceed demonstrates the	d and inserted into t n and are firmly held n using stranded wirk slot on the side of th e contact can then b ontact/wire which can edure (max. 5x).	he cavities of the connector in place. A light pull on the es with a gauge below 0.37 m he respective crimp cavity. T be easily withdrawn using a l n be repositioned/refitted as is Insulation Ø [mm] 24 0,7 - 1,5 20 0,8 - 2,0 16 1,6 - 2,8 ise exclusively crimp tools a he catalogue size tol. Inspected by Sta TADJE HOF	moulding in the re e wire assures the mm ² an insertion the ihis action compress light pull on the w s necessary. The d Interpret of the second second by HARTIN pproved by HARTIN crimp	equired correct bol is ses the ire. This rawing <u>trength [N]</u> - 28 - 60 - 135 - 135 - 135 - 135 - 135 - 135 - 135 - 28 - 60 - 135 - 28 - 60 - 135 - 13	3, 3, 3, 3, 0 60352-2) 310 08 01 / EC01557 / 14 State Final Re	5 +0,5 5 +0,5 5 +0,5 4.07.2011 elease Doc-Key / ECM 100581009/UGD/0

Α4